

Temperature/Humidity/Calendar clock 3 in 1 Thermo-hygrometer User's Manual

1.Features:

Simultaneous Indication: Temperature, Humidity, Calendar clock.

Temperature Indication: °C / °F

Max. /Min. Temperature and humidity data store function.

Calendar function, hours beep function, alarm clock, and 12/24 hour display.

Temperature Range: -50°C ~70°C (-58°F ~158°F)

Temperature Accuracy: ±1.0°C (1.8°F)

Temperature Resolution: 0.1°C (0.1°F)

Humidity Range: 10%RH~99%RH

Humidity Accuracy: ±5% (35%~75%), and else ±10%

Battery: AAA 1.5V

2.Basic Function Button:

[MODE/SET] is used to shift between the alarm and clock and set the time, alarm and calendar;

[ADJ] is used to adjust the values, turn on/off the alarm and display date;

[MAX/MIN] is used to indicate the MAX and MIN values of temperature and humidity;

[C/F] is used to select the unit of temperature between °C and °F;

[CLEAR] is used to clear the MAX and MIN values of temperature and humidity.



3.Time and Date Adjustment:

Press the [MODE/SET] for three seconds the digit on “second” will start to flash, then press [ADJ] to adjust. Press [MODE/SET] again, the digit on “hour” will start to flash, then press [ADJ] to adjust. Press [MODE/SET] again it can show 12/24 hour system, and then press [ADJ] to choose. Press [MODE/SET] again, and

then press [ADJ] to choose month. Press [MODE/SET] again, and then press [ADJ] to choose date. Press [MODE/SET] one more time to confirm all the settings.

4.Alarm Adjustment:

Press [MODE/SET] to show the alarm time, and press [MODE/SET] for three seconds the digit on “second” start to flash, and then press [ADJ] to adjust. Press [MODE/SET] again the digit on “hour” will start to flash, then press [ADJ] to adjust. Continually press [MODE/SET] twice to confirm.

Alarm on/off: Press [MODE/SET] to show the alarm time, and press [ADJ] to show the symbol of “” and then press [ADJ] again to show the symbol of “”. Press [ADJ] again, two symbols will be shown together. Continually press [ADJ] can turn on or off those functions, and at last press [MODE/SET] to confirm. When the alarm is ringing, press any button will stop the alarm.

5.Calendar Display:

When clock display press [ADJ] can show the date and it will back to clock display in 3 seconds.

6.MAX/MIN Temperature and Humidity Display:

Press [MAX/MIN] to show the MAX/ MIN values of temperature and humidity. Continuously press [MAX/MIN] for 2 seconds or press [CLEAR] can clear all the memory.

NOTE:

1. When the digital get blurred, please replace the battery. Please put the used battery into the recycling bin.
2. Operation Environment: 0°C~50°C.
3. This thermo-hygrometer is not suitable for industrial usage. It is suitable for household.